




Grablink Value

Frame grabber for one base-configuration Camera Link camera



At a Glance

- For one Camera Link Base configuration camera
- Directly compatible with hundreds of Camera Link cameras available on the market
- PCI 32-bit 33 MHz, 90 MB/s sustained delivery bandwidth
- 8-MByte on board memory
- Feature-rich set of 4 digital IO lines

Benefits

Directly compatible with hundreds of Camera Link cameras available on the market

Check out our camera compatibility page (in the Support menu) to download the relevant CamFiles

General purpose I/O lines

Compatible with a wide range of sensors and motion encoders.

High-performance DMA (Direct Memory Access)

- Direct transfer into user-allocated memory
- Hardware scatter-gather support

Flexible line-scan camera operation with the rate converter.

- The rate converter is a smart, programmable frequency multiplier/divider.
- Used with motion encoders and line-scan cameras, it allows the user to choose the aspect ratio of the pixels in the image.
- It provides a way to calibrate the acquisition chain to easily reach square (1:1 aspect ratio) pixels.

Windows drivers available

Applications

Machine Vision for the Electronic Manufacturing Industry

- High speed image acquisition for AOI, 3D SPI, 3D lead/ball inspection machines.
- Very high resolution line-scan image acquisition for Flat Panel Display inspection and solar cell inspection

Machine Vision for the General Manufacturing Industries

- High frame rate image acquisition for inspection machines
- Line-scan image acquisition for surface inspection machines
- Line-scan image acquisition for textile inspection

Machine Vision for the Printing Industry

- High speed line-scan image acquisition for printing inspection machines

Video Acquisition and Recording

- High-frame-rate video acquisition for motion analysis and recording

Specifications

Mechanical

Form Factor	PCI card
Format	Standard profile, half-length, 32-bit Conventional PCI card
Cooling method	Air-cooling
Mounting	For insertion in a standard height, 32- or 64-bit, PCI card slot
Connectors	<ul style="list-style-type: none">• 'CAMERA LINK' on bracket:<ul style="list-style-type: none">– 26-position Mini Delta Ribbon (MDR) socket– Camera Link connector• 'SYSTEM I/O' on bracket:<ul style="list-style-type: none">– 9-pin 2-row female sub-D connector– I/O lines and power output
Dimensions	L 130 mm x H 104 mm L 5.12 in x H 4.09 in

Host bus

Standard	PCI 32-bit, 33 MHz, 3.3 V and 5 V signaling
DMA	32-bit
Peak delivery bandwidth	132 MB/s
Effective (sustained) delivery bandwidth	90 MB/s (Host PC motherboard dependent)
Power consumption	Max. 3.5 W (700 mA @ +5V), excluding I/O power output

Camera / video inputs

Interface standard(s)	Camera Link
Connectors	1 Mini Delta Ribbon (MDR) Camera Link (CL)
Number of cameras	One Base camera
Line-scan cameras supported	Yes
Maximum aggregated camera data transfer rate	1.44 Gbit/s (180 MB/s)
Camera Link configuration	Base
Camera Link clock frequency	From 20 MHz up to 60 MHz
Camera types	<ul style="list-style-type: none">• Gray-scale and color (RGB and Bayer) cameras• Area-scan and line-scan cameras

Video delivery

Raw video format(s)	<ul style="list-style-type: none">• Monochrome formats: Y8, Y10, Y12, Y14, Y16• Packed RGB color formats: RGB24, RGB32• Planar RGB color formats: RGB24PL, RGB30PL, RGB36PL, RGB42PL, RGB48PL• Additional formats: BAYER8, BAYER10, BAYER12, BAYER14, BAYER16, RAW8, RAW10, RAW12, RAW14, RAW16
---------------------	--

On-board processing

On-board memory	8 MB (4 MB for image data)
-----------------	----------------------------

Image data stream processing • Unpacking of 10-/12-/14-bit to 16-bit with selectable justification to LSb or MSb

General Purpose Inputs and Outputs

Number of lines	4 I/O lines: <ul style="list-style-type: none">• 2 differential inputs (TRG)• 1 isolated output (STR)• 2 multimode inputs/outputs (A1, A2)
Usage	<ul style="list-style-type: none">• Camera and image acquisition trigger• Light strobe trigger• Camera synchronization using motion encoder• General purpose IO
Electrical specifications	<ul style="list-style-type: none">• A1, A2: Inputs or outputs, isolated up to 500 V:<ul style="list-style-type: none">– Input: compatible with TTL or 12V signals– Output: TTL, open-collector or open-emitter• TRG: LVDS trigger input• STR: TTL strobe output
Filter control	<ul style="list-style-type: none">• Glitch removal filter available on input lines used as trigger sources:• Configurable with five time constants:<ul style="list-style-type: none">– 100 ns, 500 ns and 2.5 μs for trigger/ page trigger /page end trigger sources– 100 ns, 500 ns, 2.5 μs for line trigger source
Power output	<ul style="list-style-type: none">• Non-isolated +5V, 1A and +12V, 500 mA with self-resettable fuse protection• Isolated +5V 100 mA with self-resettable fuse protection

Software

Host PC Operating System	<ul style="list-style-type: none">• Microsoft Windows 10, 8.1, 7 for x86 (32-bit) and x86-64 (64-bit) processor architectures• Linux for x86 (32-bit) and x86-64 (64-bit) processor architectures <p>Refer to release notes for details</p>
APIs	<ul style="list-style-type: none">• MultiCam 32- and 64-bit binary libraries (Windows and Linux), for ISO-compliant C/C++ compilers

Environmental conditions

Operating ambient air temperature	0 to +50 °C / +32 to +122 °F
Operating ambient air humidity	10 to 90% RH non-condensing
Storage ambient air temperature	-20 to +70 °C / -4 to +158 °F
Storage ambient air humidity	10 to 90% RH non-condensing

Certifications

Electromagnetic - EMC standards	<ul style="list-style-type: none">• European Council EMC Directive 2004/108/EC
EMC - Emission	<ul style="list-style-type: none">• EN 55022:2010 Class B
EMC - Immunity	<ul style="list-style-type: none">• EN 55024:2010 Class B• EN 61000-4-2• EN 61000-4-3• EN 61000-4-4
KC Certification	Korean Radio Waves Act, Article 58-2, Clause 3
Flammability	PCB compliant with UL 94 V-0
RoHS	European Union Directive 2011/65/EU (ROHS2)
REACH	European Union Regulation 1907/2006

WEEE

Must be disposed of separately from normal household waste and must be recycled according to local regulations

Ordering Information

Product code - Description

- 1191 - Grablink Value
-



AMERICA

Euresys Inc.

27126-B Paseo Espada - Suite 704
San Juan Capistrano, CA 92675 - United States
Phone: +1 949 743 0612
Email: sales.americas@euresys.com

EMEA

Euresys SA

Liège Science Park - Avenue du Pré Aily, 14
4031 Angleur - Belgium
Phone: +32 4 367 72 88
Email: sales.europe@euresys.com

EMEA

Sensor to Image GmbH

Lechtorstrasse 20 -
86956 Schongau - Germany
Phone: +49 8861 2369 0
Email: sales.europe@euresys.com

ASIA

Euresys Pte. Ltd.

750A Chai Chee Road - #07-15 Viva Business Park
Singapore 469001 - Singapore
Phone: +65 6445 4800
Email: sales.asia@euresys.com

CHINA

Euresys Shanghai Liaison Office

Unit 802, Tower B, Greenland The Center - No.500 Yunjin Road, Xuhui District
200232 Shanghai - China
Euresys上海联络处
上海市徐汇区云锦路500号绿地汇中心B座802室
200232
Phone: +86 21 33686220
Email: sales.china@euresys.com

JAPAN

Euresys Japan K.K.

Expert Office Shinyokohama - Nisso Dai 18 Building, Shinyokohama 3-7-18
Kouhoku-Ku, Yokohama-Shi 222-0033 - Japan
〒222-0033
神奈川県横浜市港北区新横浜3-7-18 日総第18ビル エキスパートオフィス新横浜
Phone: +81 45 594 7259
Email: sales.japan@euresys.com

More at www.euresys.com

