




# MVDK

## Machine Vision Development Kit



### At a Glance

- All major machine vision interfaces available on a single development board
- GigE Vision, CoaXPress and USB3 Vision compliant platform
- Sony IMX Pregius evaluation platform
- GigE Vision up to 10 Gb/s. CoaXPress up to CXP-12
- Support for Enclustra Mercury FPGA modules with Xilinx and Intel FPGAs

### Benefits

#### A Sensor to Image product

#### MVDK Description

S2I's MVDK (Machine Vision Development Kit) is a hardware platform that eases the evaluation and development of products based on S2I's IP Cores and using any major industrial vision interface. The MVDK base board is highly configurable through the use of FMCs (FPGA Mezzanine Cards). It provides an interface to vision sensors and enables the development of GigE Vision, USB3 Vision and CoaXPress cameras (devices), as well as the design of GigE Vision and CoaXPress hosts.

#### Hardware and Reference Design

The MVDK is delivered with an Enclustra Mercury FPGA module and an FMC interface board . They come along with a reference design for the selected transport layer interfaces. Together, they minimize development time and allow for top-notch performance at a small footprint, while leaving enough flexibility to customize the design.

#### MVDK base board features

- 2x 10/100/1000 Ethernet (PS based and PL based) (the latter is used for GigE Vision)
- USB 3.0, implemented with PTN36241BBS driver
- USB 2.0 OTG
- USB Serial
- 4 User LEDs
- 4 User Push-Buttons
- 12 Test Pins
- 1 or 2 FMC connectors to connect camera modules or additional interface modules
- HDMI Output, implemented with ADI ADV7511

#### MVDK ZX5: MVDK board with Enclustra Mercury ZX5 Module

- Xilinx Zynq-7000-series SoC FPGA 7015
- 1 GB DDR3 SDRAM
- 512 MB NAND Flash
- 64 MB quad SPI Flash
- 10/100/1000 Ethernet PHY
- Four 6.25 Gb/s transceivers

#### **MVDK XU1: MVDK board with Enclustra Mercury+ XU1 Module**

- Xilinx Zynq Ultrascale+ MPSoC XCZU6
- 2 GB DDR4 ECC SDRAM
- 64 MB quad SPI Flash
- 16 GB eMMC Flash
- 10/100/1000 Ethernet PHY
- 8+3 16 Gb/s transceivers (using both FMC connectors)

#### **MVDK SA1: MVDK board with Enclustra Mercury SA1 Module**

- Altera Cyclone V ARM Processor-based SoC FPGA
- 1 GByte DDR3L SDRAM
- 64 MB quad SPI Flash
- 10/100/1000 Ethernet PHY
- Five 3.125 Gb/s transceivers

#### **For CoaXPress development**

The MVDK delivered for CoaXPress development includes an FMC with two or four CXP-6 or CXP-12 links for device (camera) or host (frame grabber) design. The device and host reference designs are fully CoaXPress compliant and certified by the JIIA. (<http://jiia.org/en/cxp/camera005/>).

#### **For USB3 Vision development**

The MVDK available for USB3 Vision development is based on the 5-Gbit/s technology of standard USB3 components and allows for the most cost-effective high-speed camera design today. The USB3 Vision IP Core development kit is fully compliant with Genicam and certified by the AIA. This is the easiest way to start the design of a new USB3 Vision camera. The USB3 Vision interface is implemented using an FMC designed by S2I that uses a Cypress FX3 USB3 chip.

#### **For GigE Vision development**

The MVDK delivered for GigE Vision development supports the design of camera and host applications compliant with the AIA GigE Vision specification with a speed of up to 10 Gbit/s. 2.5, 5 and 10 Gbit/s applications require an S2I NBase-T FMC module.

#### **For Sony IMX development**

S2I's MVDK is compliant with Sony's IMX Pregius series of sensors, a widely used, high-quality CMOS series of imagers. S2I supports these sensors with dedicated IP to read data from and control the sensors. The reference design consists of the IMX IP Core together with a GigE Vision compliant output.

## Specifications

## Ordering Information

---

Product code - Description	• 7010 - MVDK
----------------------------	---------------

---



## AMERICA

### **Euresys Inc.**

27126-B Paseo Espada - Suite 704  
San Juan Capistrano, CA 92675 - United States  
Phone: +1 949 743 0612  
Email: sales.americas@euresys.com

## EMEA

### **Euresys SA**

Liège Science Park - Avenue du Pré Aily, 14  
4031 Angleur - Belgium  
Phone: +32 4 367 72 88  
Email: sales.europe@euresys.com

## EMEA

### **Sensor to Image GmbH**

Lechtorstrasse 20 -  
86956 Schongau - Germany  
Phone: +49 8861 2369 0  
Email: sales.europe@euresys.com

## ASIA

### **Euresys Pte. Ltd.**

750A Chai Chee Road - #07-15 Viva Business Park  
Singapore 469001 - Singapore  
Phone: +65 6445 4800  
Email: sales.asia@euresys.com

## CHINA

### **Euresys Shanghai Liaison Office**

Unit 802, Tower B, Greenland The Center - No.500 Yunjin Road, Xuhui District  
200232 Shanghai - China  
Euresys上海联络处  
上海市徐汇区云锦路500号绿地汇中心B座802室  
200232  
Phone: +86 21 33686220  
Email: sales.china@euresys.com

## JAPAN

### **Euresys Japan K.K.**

Expert Office Shinyokohama - Nisso Dai 18 Building, Shinyokohama 3-7-18  
Kouhoku-Ku, Yokohama-Shi 222-0033 - Japan  
〒222-0033  
神奈川県横浜市港北区新横浜3-7-18 日総第18ビル エキスパートオフィス新横浜  
Phone: +81 45 594 7259  
Email: sales.japan@euresys.com

More at [www.euresys.com](http://www.euresys.com)

